

SMPTE STANDARD

Carriage of Ancillary Data
Packets in an MPEG-2
Transport Stream



Table of Contents	Page
Foreword	2
Intellectual Property	2
Introduction	2
1 Scope	3
2 Conformance Notation	3
3 Normative References	3
4 MPEG-2 Transport Stream Syntax	4
4.1 PMT Signaling	4
4.1.1 stream_type	4
4.1.2 anc_data_descriptor	4
4.1.3 Registration Descriptor	4
4.2 ANC Data PES Packet	4
4.2.1 Semantics	6
Annex A Bibliography (Informative)	7

Foreword

SMPTE (the Society of Motion Picture and Television Engineers) is an internationally-recognized standards developing organization. Headquartered and incorporated in the United States of America, SMPTE has members in over 80 countries on six continents. SMPTE's Engineering Documents, including Standards, Recommended Practices and Engineering Guidelines, are prepared by SMPTE's Technology Committees. Participation in these Committees is open to all with a bona fide interest in their work. SMPTE cooperates closely with other standards-developing organizations, including ISO, IEC and ITU.

SMPTE Engineering Documents are drafted in accordance with the rules given in Part XIII of its Administrative practices.

SMPTE Standard 2038 was prepared by Technology Committee D27.

Intellectual Property

At the time of publication no notice had been received by SMPTE claiming patent rights essential to the implementation of this Standard. However, attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. SMPTE shall not be held responsible for identifying any or all such patent rights.

Introduction

This section is entirely informative and does not form an integral part of this document.

This document defines the carriage of ancillary (ANC) data within MPEG-2 Transport Streams. The mechanism provides a data pipe through which SMPTE 291M ANC data packets may be conveyed transparently through equipment that uses the MPEG-2 Transport Stream protocol. The data need not be recognized or interpreted by said equipment.

The lines used for the carriage of ANC data depend on the sample structure (e.g., SMPTE 274M for 1080 lines and SMPTE 296M for 720 lines). As a guideline for receiving equipment, the maximum possible amount of data payload to be re-embedded per line (or per field, as applicable) is $1920 \text{ samples} \times 10 \text{ bits (8 bit values are extended to 10 bits with parity and !parity)} = 19,200 \text{ bits or less than 2.4kbytes}$.

A mechanism is provided such that the ANC data will be presented frame-accurately with the corresponding video.

This mechanism is not intended for the carriage of audio, since there are already well-established mechanisms for doing that.

This mechanism is not intended to carry EDH packets.

1 Scope

This document defines the syntax and semantics for the carriage of SMPTE 291M Ancillary Data Packets in MPEG-2 Transport Stream PES packets. It supports ancillary data packets regardless of whether they originate from an SD or HD interface, or if the ANC data packet is from VANC or HANC, Y or C space. Sufficient information is provided to enable the ANC packets at the output of the decoder to be restored to their "original" locations in the serial digital video signal.

2 Conformance Notation

Normative text is text that describes elements of the design that are indispensable or contains the conformance language keywords: "shall", "should", or "may". Informative text is text that is potentially helpful to the user, but not indispensable, and can be removed, changed, or added editorially without affecting interoperability. Informative text does not contain any conformance keywords.

All text in this document is, by default, normative, except: the Introduction, any section explicitly labeled as "Informative" or individual paragraphs that start with "Note:"

The keywords "shall" and "shall not" indicate requirements strictly to be followed in order to conform to the document and from which no deviation is permitted.

The keywords, "should" and "should not" indicate that, among several possibilities, one is recommended as particularly suitable, without mentioning or excluding others; or that a certain course of action is preferred but not necessarily required; or that (in the negative form) a certain possibility or course of action is deprecated but not prohibited.

The keywords "may" and "need not" indicate courses of action permissible within the limits of the document.

The keyword "reserved" indicates a provision that is not defined at this time, shall not be used, and may be defined in the future. The keyword "forbidden" indicates "reserved" and in addition indicates that the provision will never be defined in the future.

A conformant implementation according to this document is one that includes all mandatory provisions ("shall") and, if implemented, all recommended provisions ("should") as described. A conformant implementation need not implement optional provisions ("may") and need not implement them as described.

3 Normative References

The following standards contain provisions which, through reference in this text, constitute provisions of this standard. At the time of publication, the editions indicated were valid. All standards are subject to revision, and parties to agreements based on this standard are encouraged to investigate the possibility of applying the most recent edition of the standards indicated below.

SMPTE 291M-2006, Television — Ancillary Data Packet and Space Formatting

ITU-R BT.1700 (02/05), Characteristics of Composite Video Signals for Conventional Analogue Television Systems

ITU-R BT.1120-6 (08/05), Digital Interfaces for HDTV Studio Signals

ISO/IEC 13818-1:2007(E), Information Technology — Generic Coding of Moving Pictures and Associated Audio Information: Systems

4 MPEG-2 Transport Stream Syntax

4.1 PMT Signaling

The ANC data stream shall be identified in the PMT of the MPEG-2 Program of which it is part, using the following ISO/IEC 13818-1 syntax.

4.1.1 stream_type

The stream_type shall be set to 0x06 (PES private data).

4.1.2 anc_data_descriptor

The anc_data_descriptor, shown in Table 1, shall be used in the ES loop. The tag value shall be 0xC4 (user-defined in ATSC, DVB and SCTE).

Table 1 – anc_data_descriptor syntax

Syntax	No. of bits	Mnem.	Valid Range
anc_data_descriptor() {			
descriptor_tag	8	uimsbf	0xC4
descriptor_length	8	uimsbf	0x00.. 0xFF
for (I=0; i<N; i++) {			
descriptor()			
}			
}			

4.1.2.1 Semantics

descriptor(): This structure may be used to convey additional information about the ANC data component. The use is optional and currently undefined. Compliant receive devices shall ignore unrecognized descriptors.

4.1.3 Registration Descriptor

The anc_data_descriptor_tag is in ISO/IEC 13818-1 user private data code space. The anc_data_descriptor shall be preceded by an ISO/IEC 13818-1 registration_descriptor with format_identifier set to 0x56414E43 ("VANC").

4.2 ANC Data PES Packet

The format of the ANC data PES packet is shown in Table 2.

Table 2 – Format of the ANC Data PES packet

Syntax	No. of bits	Identifier
anc_data_packet() {		
packet_start_code_prefix	24	0x000001
stream_id	8	0xBD [private_stream_1]
PES_packet_length	16	uimsbf
'10'	2	'10'
PES_scrambling_control	2	'00' [not scrambled]
PES_priority	1	bslbf
data_alignment_indicator	1	'1' [payload aligned]
copyright	1	bslbf
original_or_copy	1	bslbf
PTS_DTS_flags	2	'10' [PTS present]
ESCR_flag	1	'0' [not present]
ES_rate_flag	1	'0' [not present]
DSM_trick_mode_flag	1	'0' [not present]
additional_copy_info_flag	1	'0' [not present]
PES_CRC_flag	1	'0' [not present]
PES_extension_flag	1	'0' [not present]
PES_header_data_length	8	0x05
'0010'	4	'0010'
PTS[32..30]	3	bslbf
marker_bit	1	'1'
PTS[29..15]	15	bslbf
marker_bit	1	'1'
PTS[14..0]	15	bslbf
marker_bit	1	'1'
for (i=0; i<N; i++) {		
'000000'	6	'000000'
c_not_y_channel_flag	1	bslbf
line_number	11	uimsbf
horizontal_offset	12	uimsbf
DID	10	bslbf
SDID	10	bslbf
data_count	10	bslbf
for (j=0; j<data_count; j++) {		
user_data_word	10	bslbf
}		
checksum_word	10	bslbf
while (!bytealigned) {		
'1'	1	bslbf
}		
}		
for (i=0 ;i<N; i++) {		
stuffing_byte	8	'1111 1111'
}		
}		

Each ANC data PES packet shall contain ANC data from no more than one line. ANC data packets extracted from the same line shall be conveyed in the same ANC data PES packet.

The PTS value in the ANC data packet shall match the PTS value in the corresponding video PES packet within ± 2 ms.

In the case of field pictures, PTS values for ANC data PES packets shall match the PTS for field 1 of the frame with which the ANC data is associated. For 3:2 pull-down, the equivalent PTS values for field 1 shall be inferred if that field is not coded (due to repeat field-frame).

The PTS values for ANC lines that belong to the same field shall be identical.

4.2.1 Semantics

Except as noted below, the definition of all syntax fields shall be as defined in ISO/IEC 13818-1 (shown as gray shaded fields in Table 2). In the case of fixed value assignment, the values shall be as defined in Table 2.

c_not_y_channel_flag: For HD, this flag, when set to '1', indicates the ANC data corresponds to the color difference channel. When set to '0', this flag indicates the ANC data corresponds to the luminance channel. For SD, this flag shall be set to '0'.

line_number: This field contains the line number (as defined in ITU-R BT.1700 [SD] or ITU-R BT.1120-6 [HD]) that corresponds to this ancillary data packet. The lines that are available to convey ancillary data are as defined in the applicable sample structure specification (e.g., SMPTE 274M, SMPTE 296M, ITU-R BT.656-4), and may be further restricted per SMPTE RP 168.

horizontal_offset: This field defines the location of the ANC packet relative to SAV. 0 means that the ADF sequence begins immediately following SAV. For HD, this is in units of Y samples (e.g., the range 0 to 2199 for 1080i @ 59.94). For SD, this is in units of (27MHz) multiplexed word numbers.

DID, SDID, data_count, user_data_word, checksum_word: These fields represent the data to be reinserted as ancillary data, per SMPTE 291M. For the purposes of the "for" loop syntax counter only, only the lower 8 bits of data_count, corresponding to bits b7 (MSB) through b0 (LSB) of the 10-bit SMPTE 291M data count word, shall be used.

stuffing_byte: This is a fixed 8-bit value equal to '1111 1111' that may be inserted by a transmitting device. It may be ignored by the receiving device.

Annex A (Informative)

Bibliography

SMPTE 274M-2008, Television — 1920 x 1080 Image Sample Structure, Digital Representation and Digital Timing Reference Sequences for Multiple Picture Rates

SMPTE 296M-2001, Television — 1280 x 720 Progressive Image Sample Structure — Analog and Digital Representation and Analog Interface

SMPTE RP 168-2002, Definition of Vertical Interval Switching Point for Synchronous Video Switching

ITU-R BT.656-5 (12/07), Interfaces for Digital Component Video Signals in 525-Line and 625-Line Television Systems Operating at the 4:2:2 Level of Recommendation ITU-R BT.601